

	moXF	MODX	MODX+	MONTAGE
AWM2 Polyphony	128 mono	128 stereo	128 stereo	128 stereo
FM-X Polyphony	none	64	128	128
Flash Memory	optional, up to 1 GB	built-in, 1 GB	built-in, 1.75 GB	built-in, 1.75 GB
Outputs	Unbalanced	Unbalanced	Unbalanced	Balanced
D/A	Normal	Normal	Normal	Pure Analog Circuit
Keyboard Action	Semi weighted(61) GHS(88)	Semi weighted(61/76) GHS(88)	Semi weighted(61/76) GHS(88)	FSX (61/76) BH (88)
Aftertouch	no	no	no	Yes (Channel)
Sliders/Knobs	none/8	4/4	4/4	8/8
Scenes/Scene Switches	6/6	8/4	8/4	8/8
Pitch/Mod Wheels	Plastic	Plastic	Rubber-coated	Rubber-coated
Ribbon	none	-	-	Yes
Motion Control	No	Yes	Yes	Yes
Live Sets	No	Yes	Yes	Yes
Screen	240 x 64 dot, backlit LCD	7" TFT Color Wide VGA LCD touch screen	7" TFT Color Wide VGA LCD touch screen	7" TFT Color Wide VGA LCD touch screen
Seamless Sound Switching	No	4 Part	4 Part	8 Part